



PS MANUAL

## BCS SWITCHMODE BATTERY CHARGERS

1.0 Model            **BCS-1260C**

2.0 Description

12 Volt 60 Amp Fully Automatic SwitchMode Battery Charger



Durst Industries Australia Pty. Ltd.

[durst.com.au](http://durst.com.au)

Phone: +61 2 9660 1755

Unit 1, 11 Packard Avenue  
Castle Hill NSW 2154 Australia





### 3.0 Features

- Fully Automatic, Fast and Safe.
- Overcharging Protection: Yes with Current limiting
- Short Circuit, Spike and Surge Protection
- Isolated Output Terminals
- Programmable UO Voltage to suit battery type
- Switchable 4H or 8H UO Charging phase
- Three stage Charging indicator LED's
- Mute button for quieter operation
- Eliminates Sulphation
- Compact and Lightweight
- Suitable also as a Power Supply
- NASA Developed Technology
- Australian Electrical Standard & EMC Compliant

### 4.0 Physical and Dimensional Properties

- Each unit weighs approximately 5.0 Kg
- Width 229 mm
- Length 330 mm
- Height 107 mm
- Carton Dimensions: 265 x 400 x 145

### 5.0 Performance

- Voltage 207-253 Volt
- Frequency 50/60 Hz
- Battery Size Ahr 180Ahr - 600Ahr
- Output Current: 60 Amps
- Number of Channels 3
- Charging Voltage 14.4 - 14.8 VDC to suit GEL AGM Flooded Calcium
- Float Charge 13.8 VDC to suit GEL AGM Flooded Calcium
- Line/ Load regulation: 0.1% @ input voltage range/ 1.5% @ output current No Load to Full Load. Over 85% Efficiency
- Battery Connections: Heavy Terminal blocks ( Cables to order)

### 6.0 Uses

- Premium Switchmode Battery Charger.
- Suitable for Automotive, Marine, Mobile Home or Caravan, Mobility Appliances, Solar, Deep Cycle, UPS Standby.

### 7.0 Documentation

- Bar Code Number: **9346080001324**
- Product Specification Manual – PS 145
- Work Instruction Manual - WI 145
- Product Costing Manual - PC 145

