



DATA SHEET

BOOSTER 8

PORTABLE JUMP STARTER

MODEL

› BOOSTER 8

DESCRIPTION

› 12 Volt and 24 Volt
Portable Jump Starter

PERFORMANCE

At 12 Volts

› Cold Cranking Amps: CCA 1,200
› Peak Amps: PA 7,600

At 24 Volts

› Cold Cranking Amps: CCA 600
› Peak Amps: PA 3,800

Battery

› 2 x 22 Ah Durst 212 HP AGM,
Local stock, user serviceable



Durst Industries (Aust.) Pty Ltd.
1/11 Packard Ave. Castle Hill
NSW 2154 Australia

 DURST.COM.AU
 SALES@DURST.COM.AU
 **INTL +61 2 9660 1755**



FEATURES

- › Designed in Australia for Australian Conditions and Climate.
- › Complies with WHS Regulations.
- › Powder Coated Steel Cabinet.
- › Reverse Polarity Protection Buzzer - LED Warning Light.
- › Anti Spike Protection, Local stock, user serviceable.
- › Battery Isolation Switch - 12Volt - Off - 24 Volt
Local stock, user serviceable.
- › Voltage Selection and Indicator Light.
- › Long Life - and maintenance free.
- › Fuse: Ignition Protected Auto Reset - in case of short circuit.
Maintenance Free, no replacement required.

PHYSICAL AND DIMENSIONAL PROPERTIES

- › Each unit weighs approximately 20 Kg
- › Width 280 mm
- › Length 260 mm
- › Height 360 mm
- › Cable Length 150 cm
- › Cable Size 70 mm² (AWG2/0) Superflex, dual insulated pure multi-strand copper
- › Anderson to Clamp (Standard),
Anderson to Anderson and Anderson to CAT (Optional extras)
- › Clamps: 1000A Insulated Extra heavy duty, nickel plated copper

FUNCTIONS

- › Multifunction Digital Volt Meter
- › Warning Buzzer
- › Computer Safe
- › Optional trolley available
- › DC Charger: Optional
- › AC Charger: Automatic, Durst BCS-A1206

SERVICEABILITY

- › User serviceable, does not void warranty