



PS MANUAL

BCS-BATTERY CHARGERS

1.0 Model **BCS-A1225**

2.0 Description

12 Volt 25Amp SmartCharger Battery Charger



Durst Industries Australia Pty. Ltd.

durst.com.au

Phone: +61 2 9660 1755

Unit 1, 11 Packard Avenue
Castle Hill NSW 2154 Australia



3.0 **Features**

- Fully Automatic, Fast and Safe.
- Overcharging Protection.
- Short Circuit Protection
- High Efficiency
- Three stage Charging indicator LED's
- Eliminates Sulphation
- Compact and Lightweight
- Leads and Battery Clamps
- Australian Electrical Standard & EMC Compliant
- Available with Optional plug to suit Mobility Scooters, wheel chairs etc

4.0 **Physical and Dimensional Properties**

- Each unit weighs approximately 2.1 Kg
- Width 152 mm
- Length 225 mm
- Height 70 mm
- Carton Dimensions: 340 x 250 x 115
- Colour: Red

5.0 **Performance**

- Voltage 200-240 Volt
- Frequency 47-63 Hz
- Output Current: 25 Amps Dual
- Boost Voltage 14.4 Volts
- Float Voltage 13.7 Volts
- Wattage: 367W
- Battery size Ahr 60 Ahr - 300 Ahr

6.0 **Uses**

- SmartCharger Battery Charger.
- Suitable for Automotive, Marine, Mobile Home or Caravan, Mobility Appliances, Golf Carts, Solar, Deep Cycle, UPS Standby.

7.0 **Documentation**

- Bar Code Number: **9346080001454**
- Product Specification Manual – PS 158
- Work Instruction Manual - WI 158
- Product Costing Manual - PC 158

