



PS MANUAL

INDUSTRIAL WORKSHOP BATTERY CHARGERS

1.0 Model **BC-460**

2.0 Description

6 Volt, 12 Volt and 24 Volt Battery Charger



Durst Industries Australia Pty. Ltd.

durst.com.au

Phone: +61 2 9660 1755

Unit 1, 11 Packard Avenue
Castle Hill NSW 2154 Australia



3.0 Features

- Designed in Australia for Australian Conditions and Climate.
- Powder Coated Steel Cabinet with cooling vents for maximum air flow.
- Reverse Polarity Protection Buzzer - LED Warning Light.
- Circuit Breaker on DC side, resettable Circuit Breaker for AC side.
- Heavy Duty Mains power lead 3.0m (Standard 10Amp Plug Top)
- Colour Coded Battery Clamps with 2.5m Leads and Bridging Straps
- Ultra fast Silicone Diode, specially designed Heat Sink for Jump Starting.
- Fan to keep Transformer and Diode Rectifier cool under heavy loads
- Transformer: Copper Magnet wire, high grade Silicone laminations
- Large easy to read coloured Instrument scale.
- Complies with **AS3193-1984** Transformer Type battery Chargers.
- Wide Moulded handle for easy carrying
- Switch with 11 Position Current Control / Indicator
- Switch with 3 Position Voltage Selector / Indicator

4.0 Physical and Dimensional Properties

- Each unit weighs approximately 25 Kg
- Width 260 mm
- Length 370 mm
- Height 370 mm
- Cable Length 2.5 m
- Cable Size 16mm².

5.0 Performance

- Voltage 220-240 Volt
- Frequency 50/60 Hz
- Jump Start Capacity 600 Amp
- AC Current Primary 4.3 Amps @ 60Amps Continuous
- AC Current Primary 5.6 Amps @ 80Amps Continuous.
- Secondary Continuous 6 Volts Max 60Amps - Intermittent 6 Volts Max 80Amps
- Secondary Continuous 12 Volts Max 60Amps - Intermittent 12 Volts Max 80Amps
- Secondary Continuous 24 Volts Max 30Amps - Intermittent 24 Volts Max 40Amps

6.0 Uses

- Portable Battery Charger.
- Suitable for Car/Truck dealer workshops, Panel Beaters, Bus repairers, Mining Companies, Aviation, Defence, Councils, TAFE, Hire Companies, Auction Yards.

7.0 Documentation

- Bar Code Number: **9346080000457**
- Product Specification Manual -PS 19
- Work Instruction Manual - WI 19
- Product Costing Manual - PC 19

