



PS MANUAL

## PORTABLE JUMP STARTER

1.0 Model **BJC-4000AP RHINO-AP**

2.0 Description

12 Volt and 24 Volt Portable Jump Starter Anderson Plug



Durst Industries Australia Pty. Ltd.

[durst.com.au](http://durst.com.au)

Phone: +61 2 9660 1755

Unit 1, 11 Packard Avenue  
Castle Hill NSW 2154 Australia





## PS MANUAL

### 3.0 Features

- Designed in Australia for Australian Conditions and Climate.
- Complies with WHS Regulations.
- Powder Coated Steel Cabinet.
- Reverse Polarity Protection Buzzer - LED Warning Light.
- Anti Spike Protection
- Battery Isolation Switch - **12Volt - Off - 24 Volt**
- Voltage Selection and Indicator Light.
- Will Jump start vehicles - with dead flat Batteries.
- Long Life - and maintenance free.
- Fuse protected - in case of short circuit.
- Aircraft Models for various Voltages
- Custom Modifications available on request.

### 4.0 Physical and Dimensional Properties

- Each unit weighs approximately 19 Kg
- Width 330 mm
- Length 240 mm
- Height 370 mm
- Cable Length 1.8 m
- Cable Size 35mm<sup>2</sup>.

### 5.0 Performance

#### At 12 Volts

- Cold Cranking Amps: **CCA 680**
- Peak Amps: **PA 4,400**

#### At 24 Volts

- Cold Cranking Amps: **CCA 340**
- Peak Amps: **PA 2,200**
- Charger: Automatic SmartCharger **BCS-A 2404** 24 Volts 4 Amps

### 6.0 Uses

- Portable high capacity mobile jump starter.
- Suitable for Car/Light Commercial vehicle dealer workshops, Panel Beaters, Mini Bus repairers, Mining Companies, Aviation, Defence, Councils, TAFE, Hire Companies, Auction Yards.

### 7.0 Documentation

- Bar Code Number: **9346080000259**
- Product Specification Manual - PS 10
- Work Instruction Manual - WI 10
- Product Costing Manual - PC 10

