

PS MANUAL

# **MOBILE JUMP STARTER**

1.0 Model BJT-201 SCORPION 24

2.0 <u>Description</u>

24 Volt Mobile Jump Starter.



Durst Industries Australia Pty. Ltd. durst.com.au Phone: +61 2 9660 1755

Unit 1, 11 Packard Avenue Castle Hill NSW 2154 Australia







## 3.0 Features

- Designed in Australia for Australian Conditions and Climate.
- Complies with WHS Regulations.
- Powder Coated Steel Cabinet.
- Reverse Polarity Protection Buzzer LED Warning Light.
- Large Pneumatic Wheels easy to move around.
- Anti Spike Protection
- Battery Isolation Switch 24Volt Off
- Voltage Selection and Indicator Light.
- Will Jump start vehicles with dead flat Batteries.
- Long Life and maintenance free.
- Fuse protected in case of short circuit.

#### 4.0 Physical and Dimensional Properties

- Each unit weighs approximately 57 Kg
- Width 570 mm
- Length 330 mm
- Height 620 mm
- Cable Length 2.0 m
- Cable Size Primary 70mm<sup>2</sup>. **LS-704-AP350RD**

## 5.0 Performance

#### At 24 Volts

Cranking Amps: CA 980Cold Cranking Amps: CCA 800

Peak Amps est.: PA 3,500

• Charger; Automatic SmartCharger BCS-A2412 24 Volts 12 Amps

## 6.0 <u>Uses</u>

- Portable high capacity mobile jump starter.
- Suitable for Car/Truck dealer workshops, Panel Beaters, Bus repairers, Mining Companies, Aviation, Defence, Councils, TAFE, Hire Companies, Auction Yards.

# 7.0 <u>Documentation</u>

• Bar Code Number: 9346080000364

Product Specification Manual - PS 04

Work Instruction Manual - WI 04

• Product Costing Manual - PC 04

