

PS MANUAL

CARBON PILE BATTERY LOAD TESTERS

1.0 <u>Model</u> BT-2003FD

2.0 <u>Description</u>

6 Volt and 12 Volt Carry Version Battery Load Tester



Durst Industries Australia Pty. Ltd. durst.com.au Phone: +61 2 9660 1755

Unit 1, 11 Packard Avenue Castle Hill NSW 2154 Australia



PS MANUAL



3.0 <u>Features</u>

- Portable Battery Load Tester.
- Digital Volt and Amp meter
- Wide Moulded handle for easy carrying
- Large rubber feet to protect unit on rough surfaces
- Cooling vents for maximum air flow
- Fully insulated colour coded safety Clamps
- Powder coated Steel cabinet (Yellow)
- Complies with Australian Standards AS3100
- Designed in Australia
- Custom Modifications available on request

4.0 Physical and Dimensional Properties

- Each unit weighs approximately 7.0 Kg
- Width 370 mm
- Length 240 mm
- Height 310 mm
- $2 \times LS-100 = Lead Set 25mm^2 + Trace Cable 1.5m Long$
- 100Amp Clamps (Continuous)

5.0 <u>Performance</u>

- Output Voltage 6 Volt and 12 Volt
- Load Current 0 500 Amps
- Cold Cranking Amps CCA: 1000
- Amp hour Current Ah: 140

6.0 <u>Uses</u>

• Suitable for UPS Systems, GPU, Solar Power Systems, large Battery banks or Defence applications.

7.0 <u>Documentation</u>

- Bar Code Number: 934608000808
- Product Specification Manual PS 54
- Work Instruction Manual WI 54
- Product Costing Manual PC 54

